



Strumenti per l'Espresso

*radiofonica*

**AUTOMATIC**  
2 gr



Optional:  
lighting cup's LED  
and **NEW** Digit Chrono

It's inspired by the radio orchestra.

Born almost a century ago allowed many people to be able to listen to real orchestra that previously could not attend. With the same spirit Radiofonica is born as a traditional machine that wants to give an easier and simpler opportunity to many more people all around the World to enjoy a good and traditional coffee extraction.



## AUTOMATIC

2 gr

### TECHNICAL FEATURES

### AUTOMATIC

Espresso coffee and cappuccino machine with thermosiphonic system	2gr
E 61 <b>raised</b> brewing groups (filter holder Ø 58 mm)	●
Frame of satined stainless steel AISI 304	●
Boiler of copper with tap for manual discharge, pipes of copper and pipe fittings of brass	●
Dual gauges for boiler and pump pressure	●
<b>Automatic</b> boiler water loading	●
Programmable portion control / Single group washing	●
Built-in RPM motor pump with <b>AIR</b> cooling / Fluid-o-Tech rotary pump	●
Touchpad for each group with pilot lights for activated brewing buttons:	●
4 volumetric metering selections programmable from the touchpad directly, 1 programming button and 1 hot water button	●
LED lights on the back panel	●
Glass tube for boiler water level	●
2 multidirectional stainless steel steam wands with manual control from the <b>joystick taps</b>	●
1 multidirectional stainless steel hot water wand with manual control from its dedicated button on the touchpad	●



blue Tiffany



white



rust brown



black

standard color options

### OPTIONAL ON DEMAND

<b>Digit Chrono</b>	●
Lighting cup's LED	●
White filter holders for 1 and 2 cups	●
Nut wood kit: filter holders and knobs	●
<b>Color options and aesthetic customisation</b>	●

### TECHNICAL DATA

		2 gr
Voltage/Power	220 - 240 V (1F) / 400 V (3F)	3900 W
Frequency	Hz	50 - 60
Boiler	Lt	11,5
Length	mm	720
Width	mm	505
Height	mm	520
Net weight	Kg	78

D.I.D. srl reserves the right to modify the appliances presented in this publication without notice.